

ECE 401 Signal and Image Analysis

Homework 1

UNIVERSITY OF ILLINOIS
Department of Electrical and Computer Engineering

Assigned: Tuesday, 8/25/2020; Due: Monday, 8/31/2020
Reading: *DSP First* Appendix A

Problem 1.1

Find $\angle z$ as a function of a and b .

$$z = e^{ja} + e^{jb} \quad (1.1-1)$$

Problem 1.2

Evaluate this integral:

$$\int_0^T e^{at} dt \quad (1.2-1)$$

Problem 1.3

In MP1, one of the filters you'll create is a local averaging filter. A local averaging filter produces an output $y[n]$, at time n , which is the average of the previous N samples of $x[m]$:

$$y[n] = \frac{1}{N} \sum_{m=n-(N-1)}^n x[m] \quad (1.3-1)$$

(a) First, consider what happens if $x[m]$ is a pure tone with a period of T :

$$x[m] = \cos\left(\frac{2\pi m}{T}\right)$$

Suppose that the averaging window, N , is exactly an integer multiple of T . For example, suppose that $N = 3T$. Draw a picture of $x[m]$ as a function of m , and shade in the regions that would be added together by the summation in Eq. (1.3-1) in order to compute $y[0]$. Argue based on your figure (with no calculations at all) that $y[0] = 0$.

(b) Adding up the samples of a cosine is easy when N is an integer multiple of T , but hard otherwise. It's actually much easier to add the samples of a complex exponential, because we can use the standard geometric series formula (https://en.wikipedia.org/wiki/Geometric_series#Formula). Use that formula to find $y[0]$ when

$$x[m] = e^{j2\pi m/T}$$

Your result should have the form $y[0] = (1 - a)/(1 - b)$ for some a and b that depend on π , N , and T , but not on m or n .